



Conductor material _____	Copper tinned
Gauge _____	AWG 28/7 0.089 mm ²
Voltage rating _____	300 V _{r.m.s.}
Current rating _____	1.3 A at 10 °C rise above ambient
Capacity unbalanced _____	45.9 pF/m
Impedance unbalanced _____	105 Ω
Propagation delay _____	4.9 ns/m nominal
Insulation material _____	PVC
Temperature rating (operating) _____	-20 °C ... + 105 °C
Temperature rating (static) _____	-30 °C ... + 105 °C
Flammability rating _____	Flame retardant VW-1
Insulation resistance _____	> 10 ⁴ MΩ/km